

E-Cored Choke Details

These use a high quality, soft iron core with a large air gap and resemble a transformer in appearance.

Dimensions for the Square 147 bobbin are: 60mm (L) x 95mm (W) x 56mm (H)

An integral U-clamp for fixing by M5 bolts spaced 82mm apart is included.

E-Core chokes must not be mounted onto a ferrous substrate.

DESCRIPTION	BOBBIN TYPE	TERMINATION LENGTH	WIRE SIZE
NO.1 E-CORE CHOKE 12.00 mH, 1R2	SQUARE 147	100 MM	0.71 MM
NO.2 E-CORE CHOKE 7.00 mH, 0R6	SQUARE 147	100 MM	0.95 MM
NO.3 E-CORE CHOKE 15.00 mH, 1R6	SQUARE 147	100 MM	0.71 MM
NO.4 E-CORE CHOKE 4.00 mH, 0R5	SQUARE 147	100 MM	0.95 MM
NO.5 E-CORE CHOKE 20.00 mH, 1R8	SQUARE 147	70 MM	0.71 MM
NO.6 E-CORE CHOKE 7.00 mH, 1R0	SQUARE 147	70 MM	0.71 MM
NO.7 E-CORE CHOKE 12.00 mH, 1R2	SQUARE 147	70 MM	0.71 MM
NO.8 E-CORE CHOKE 20.00 mH, 1R8	SQUARE 147	100 MM	0.71 MM
NO.9 E-CORE CHOKE 6.00 mH, 0R6	SQUARE 147	100 MM	0.95 MM
NO.10 E-CORE CHOKE 30.00 mH, 2R4	SQUARE 147	100 MM	0.71 MM
NO.11 E-CORE CHOKE 13.00 mH, 1R4	SQUARE 147	100 MM	0.71 MM
NO.12 E-CORE CHOKE 8.50 mH, 1R0	SQUARE 147	100 MM	0.71 MM
NO.13 E-CORE CHOKE 5.00 mH, 0R5	SQUARE 147	100 MM	0.95 MM
NO.14 E-CORE CHOKE 10.00 mH, 1R2	SQUARE 147	100 MM	0.71 MM
NO.17 E-CORE CHOKE 2.50 mH, 0R4	SQUARE 147	100 MM	0.95 MM
NO.18 E-CORE CHOKE 3.00 mH, 0R4	SQUARE 147	100 MM	0.95 MM
NO.19 E-CORE CHOKE 6.60 mH, 0R6	SQUARE 147	100 MM	0.95 MM
NO.20 E-CORE CHOKE 2.00 mH, 0R3	SQUARE 147	100 MM	0.95 MM
NO.21 E-CORE CHOKE 9.50 mH, 0R8	SQUARE 147	70 MM	0.95 MM
NO.22 E-CORE CHOKE 14.00 mH, 1R5	SQUARE 147	100 MM	0.71 MM
NO.23 E-CORE CHOKE 17.00 mH, 1R8	SQUARE 147	100 MM	0.71 MM
NO.24 E-CORE CHOKE 4.50 mH, 0R4	SQUARE 147	240 MM	1.06 MM
NO.25 E-CORE CHOKE 3.15 mH, 0R27	SQUARE 147	240 MM	1.25 MM